

Review Article

Controllability of Impulsive Neutral Functional Differential Inclusions in Banach Spaces

X. J. Wan, Y. P. Zhang, and J. T. Sun

Department of Mathematics, Tongji University, Shanghai 200092, China

Correspondence should be addressed to Y. P. Zhang; zhangyinping@tongji.edu.cn

Received 10 October 2012; Revised 25 December 2012; Accepted 21 January 2013

Academic Editor: Ryan Loxton

Copyright © 2013 X. J. Wan et al. This is an open access article distributed under the Creative Commons Attribution License, which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

We investigate the controllability of impulsive neutral functional differential inclusions in Banach spaces. Our main aim is to find an effective method to solve the controllability problem of impulsive neutral functional differential inclusions with multivalued jump sizes in Banach spaces. Based on a fixed point theorem with regard to condensing map, sufficient conditions for the controllability of the impulsive neutral functional differential inclusions in Banach spaces are derived. Moreover, a remark is given to explain less conservative criteria for special cases, and work is improved in the previous literature.

1. Introduction

During the last decade, differential inclusions [1–3] were well known for applications to mechanics, engineering, and so on. Impulsive differential equations [4–9] were important in the study of physical fields. Ahmed [10] first introduced three different models of impulsive differential inclusions and studied the existence of them, respectively. From then on, there have been many focuses on various properties of impulsive differential inclusions, see [11–17] and references therein.

Controllability is one of the primary problems in control theory [11, 13, 14, 17–24]. Study on controllability has always been considered as a hot topic given its numerous applications to mechanics, electrical engineering, medicine, biology, and so forth. Because of their various application backgrounds, there were a number of researches on controllability of differential inclusions, see [11, 13, 14, 17]. Controllability of impulsive functional differential inclusions is an attractive subject, thanks to their outstanding performance in applications. But as far as we are concerned, there were very few results on controllability of the model with multivalued jump sizes [13]. As for the third model initiated by Ahmed [10], we were impressed by the statement that the model of differential inclusions with multi-valued jump sizes may arise under many different situations, for example, in case of

a control problem where one wishes to control the jump sizes in order to achieve certain objectives. In this paper, we aim to find an effective method to solve the controllability problem of impulsive neutral functional differential inclusions with multi-valued jump sizes in Banach spaces.

Liu [11] studied impulsive neutral functional differential inclusions in Banach spaces. However, to the best of our knowledge, there has not any result considering the controllability of the impulsive neutral functional differential inclusions with multi-valued jump sizes in Banach spaces. This work is both challenging and interesting, since our systems are more general than those studied ever before. Based on a fixed point theorem with regard to condensing map, we work out the sufficient conditions for the controllability of impulsive neutral functional differential inclusions in Banach spaces. In [11], Liu considered the controllability basing on Martelli's fixed point theorem [25]. He took advantage of the statement that a completely continuous map is a condensing map. However, condensing map may not be completely continuous. We notice this inequality and consider the controllability on the strength of a special property of Kuratowski measure of noncompactness in Banach spaces. Due to the property, we are allowed to prove that a map is condensing according to its definition. When jumps are single-valued maps in our system, the system degenerates into the system (1.1) in [11]. At this time, less conservative criteria can be

(A₁) The linear operator $W : L^2(J, U) \rightarrow X$ defined by

$$Wu = \int_0^b T(b-s)Bu(s)ds \quad (4)$$

has an inverse operator W^{-1} , which takes value in $L^2(J, U)/\ker W$. And W^{-1} is bounded. There exist positive constants M_2 and M_3 satisfying $\|B\| \leq M_2$ and $\|W^{-1}\| \leq M_3$.

(A₂) For each $k \in \{1, 2, \dots, m\}$, there is a positive constant α_k , such that $\|I(x(t_k^-))\| = \sup\{|\mathcal{I}_k(x(t_k^-))| : \mathcal{I}(x(t_k^-)) \in I(x(t_k^-))\} \leq \alpha_k$ for all $x \in X$.

(A₃) There exist constants $a_1, a_2, b_1,$ and b_2 , satisfying $\|Ag(t, \chi)\| \leq a_1\|\chi\|_{\mathfrak{B}_h} + a_2, |g(t, \chi)| \leq b_1\|\chi\|_{\mathfrak{B}_h} + b_2,$ and $t \in J, \chi \in \mathfrak{B}_h$.

(A₄) $F : J \times \mathfrak{B}_h \rightarrow P_{bd,cv,cl}(X); (t, \chi) \mapsto F(t, \chi)$ is measurable with respect to t for every $\chi \in \mathfrak{B}_h$, upper semicontinuous with respect to χ for every $t \in J$, and for every fixed $\chi \in \mathfrak{B}_h$

$$S_{F,\chi} = \{f \in L^1(J, X) : f(t) \in F(t, \chi), \text{ a.e. } t \in J\} \quad (5)$$

is nonempty, or equivalently, $\inf\{|f| : f(t) \in F(t, \chi)\} \in L^1\{J, X\}$.

(A₅) There is an integrable function $\varphi : J \rightarrow [0, \infty)$ and a continuous and nondecreasing function $\psi : [0, \infty) \rightarrow (0, \infty)$, such that

$$\|F(t, \chi)\| = \sup\{|f| : f \in F(t, \chi)\} \leq \varphi(t)\psi(\|\chi\|_{\mathfrak{B}_h}), \quad (6)$$

$$t \in J, \chi \in \mathfrak{B}_h.$$

Lemma 7 (see [28]). *Let I be a compact real interval, and let E be a Banach space. Let F be a multivalued map satisfying (A₄), and let Γ be a linear continuous mapping from $L^1(I, E) \rightarrow C(I, E)$. Then the operator*

$$\begin{aligned} \Gamma \circ S_F : C(I, E) &\longrightarrow P_{bd,cv,cl}(C(I, E)), x \\ &\longmapsto (\Gamma \circ S_F)(x) = \Gamma(S_{F,x}) \end{aligned} \quad (7)$$

is a closed graph operator in $C(I, E) \times C(I, E)$.

We denote the Banach space $\mathfrak{B}_b = \{x(t) : (-\infty, b] \rightarrow X : x_k \in C(J_k, X), k = 1, 2, \dots, m, \text{ such that } x \text{ is left continuous and right limits}\}$, with seminorm defined by $\|x\|_{\mathfrak{B}_b} := \|x_0\|_{\mathfrak{B}_h} + \sup_{0 \leq s \leq b} |x(s)|$, where x_k is the restriction of x to $J_k = (t_k, t_{k+1}]$.

Lemma 8. *If $x \in \mathfrak{B}_b$ and $\eta = \int_{-\infty}^0 h(s)ds < +\infty$, then for $x_t \in \mathfrak{B}_h, \eta|x(t)| \leq \|x_t\|_{\mathfrak{B}_h} \leq \|x_0\|_{\mathfrak{B}_h} + \eta \sup_{0 \leq s \leq t} |x(s)|$ holds.*

Proof. On the one hand, we have

$$\begin{aligned} \|x_t\|_{\mathfrak{B}_h} &= \int_{-\infty}^0 h(s) \sup_{s \leq \theta \leq t} |x_t(\theta)| ds \\ &= \int_{-\infty}^0 h(s) \sup_{t+s \leq \theta \leq t} |x(\theta)| ds \\ &= \int_{-\infty}^{-t} h(s) \sup_{t+s \leq \theta \leq t} |x(\theta)| ds \\ &\quad + \int_{-t}^0 h(s) \sup_{t+s \leq \theta \leq t} |x(\theta)| ds \\ &\leq \int_{-\infty}^{-t} h(s) \left[\sup_{t+s \leq \theta \leq 0} |x(\theta)| + \sup_{0 \leq \theta \leq t} |x(\theta)| \right] ds \\ &\quad + \int_{-t}^0 h(s) \sup_{0 \leq \theta \leq t} |x(\theta)| ds \\ &\leq \int_{-\infty}^{-t} h(s) \sup_{t+s \leq \theta \leq 0} |x(\theta)| ds \\ &\quad + \int_{-\infty}^0 h(s) \sup_{0 \leq \theta \leq t} |x(\theta)| ds \\ &\leq \int_{-\infty}^{-t} h(s) \sup_{s \leq \theta \leq 0} |x(\theta)| ds + \eta \sup_{0 \leq s \leq t} |x(s)| \\ &\leq \int_{-\infty}^0 h(s) \sup_{s \leq \theta \leq 0} |x(\theta)| ds + \eta \sup_{0 \leq s \leq t} |x(s)| \\ &= \|x_0\|_{\mathfrak{B}_h} + \eta \sup_{0 \leq s \leq t} |x(s)|. \end{aligned} \quad (8)$$

On the other hand, $\|x_t\|_{\mathfrak{B}_h} = \int_{-\infty}^0 h(s) \sup_{s \leq \theta \leq 0} |x_t(\theta)| ds \geq |x_t(0)| \int_{-\infty}^0 h(s) ds = \eta|x(t)|$.

The proof is thus completed. \square

For any $x_1 \in X$, we design the control function $u(t)$ in system (1) as

$$\begin{aligned} u(t) &= W^{-1} \left\{ x_1 - T(b) [\phi(0) - g(0, \phi)] - g(b, x_b) \right. \\ &\quad - \int_0^b AT(b-\xi)g(\xi, x_\xi) d\xi \\ &\quad \left. - \int_0^b T(b-\xi)f(\xi) d\xi \right. \\ &\quad \left. - \sum_{k=1}^m T(b-t_k) \mathcal{I}_k(x(t_k^-)) \right\} (t). \end{aligned} \quad (9)$$

Then we consider the multi-valued function $\mathcal{F} : \mathfrak{B}_b \rightarrow 2^{\mathfrak{B}_b}$, for any $x \in \mathfrak{B}_b$,

$$\mathcal{F}x(t) = \begin{cases} \phi(t), & t \in (-\infty, 0] \\ T(t) [\phi(0) - g(0, \phi)] + g(t, x_t) \\ \quad + \int_0^t AT(t-s)g(s, x_s) ds \\ \quad + \int_0^t T(t-s)f(s) ds \\ \quad + \int_0^t T(t-s)(Bu)(s) ds \\ \quad + \sum_{0 < t_k < t} T(t-t_k)\mathcal{F}_k(x(t_k^-)), & t \in J, \end{cases} \quad (10)$$

where $u(t)$ is described by (9), $f(t) \in S_{F,x}$, $\mathcal{F}_k(x(t_k^-)) \in I_k(x(t_k^-))$.

If we define function $\tilde{\phi} : (-\infty, b] \rightarrow \mathfrak{B}_b$ as

$$\tilde{\phi}(t) = \begin{cases} \phi(t), & t \in (-\infty, 0], \\ T(t)\phi(0), & t \in [0, b], \end{cases} \quad (11)$$

where $\phi(t) \in \mathfrak{B}_h$, and denote $y(t) = x(t) - \tilde{\phi}(t)$, then $x(t)$ is a mild solution of system (1) if and only if $y_0 = 0$ and

$$y(t) = -T(t)g(0, \phi) + g(t, x_t) + \int_0^t AT(t-s)g(s, x_s) ds + \int_0^t T(t-s)f(s) ds + \int_0^t T(t-s)(Bu)(s) ds + \sum_{0 < t_k < t} T(t-t_k)\mathcal{F}_k(x(t_k^-)), \quad t \in J, \quad (12)$$

where $x_t = y_t + \tilde{\phi}_t$, $x(t_k^-) = y(t_k^-) + \tilde{\phi}(t_k^-)$.

Now we denote $\mathfrak{B}_b^0 = \{y(t) \in \mathfrak{B}_b : y_0 = 0 \in \mathfrak{B}_h\}$, and define norm $\|y(t)\|_{\mathfrak{B}_b^0} = \sup_{0 \leq t \leq b} |y(t)|$, thus \mathfrak{B}_b^0 is a Banach space. Then we can define another multi-valued function $\mathcal{F}_1 : \mathfrak{B}_b^0 \rightarrow 2^{\mathfrak{B}_b^0}$; $\mathcal{F}_1 y(t) = \mathcal{F}x(t) - \tilde{\phi}(t)$, so

$$\mathcal{F}_1 y(t) = \begin{cases} 0, & t \in (-\infty, 0] \\ -T(t)g(0, \phi) + g(t, x_t) \\ \quad + \int_0^t AT(t-s)g(s, x_s) ds \\ \quad + \int_0^t T(t-s)f(s) ds \\ \quad + \int_0^t T(t-s)(Bu)(s) ds \\ \quad + \sum_{0 < t_k < t} T(t-t_k)\mathcal{F}_k(x(t_k^-)), & t \in J, \end{cases} \quad (13)$$

where $u(t)$ is the same as that in (10). Thus \mathcal{F} has a fixed point in \mathfrak{B}_b if and only if \mathcal{F}_1 has a fixed point in \mathfrak{B}_b^0 , $y(t) = x(t) - \tilde{\phi}(t)$.

Let $\mathfrak{B}_r = \{y(t) \in \mathfrak{B}_b^0 : \|y(t)\|_{\mathfrak{B}_b^0} = \sup_{0 \leq s \leq b} |y(s)| \leq r\}$, and r is a positive constant. It is true that \mathfrak{B}_r is a closed subspace of \mathfrak{B}_b^0 , so \mathfrak{B}_r is also a Banach space. Next we show that \mathcal{F}_1 has a fixed point in \mathfrak{B}_r .

Lemma 9. \mathcal{F}_1 is bounded, convex, and closed on \mathfrak{B}_r .

Proof. (I) \mathcal{F}_1 is bounded on \mathfrak{B}_r . Let $y \in \mathfrak{B}_r$, thanks to Lemma 8,

$$\begin{aligned} \|x_t\|_{\mathfrak{B}_h} &\leq \|y_t\|_{\mathfrak{B}_h} + \|\tilde{\phi}_t\|_{\mathfrak{B}_h} \\ &\leq \eta \sup_{0 \leq s \leq t} |y(s)| + \|y_0\|_{\mathfrak{B}_h} \\ &\quad + \eta \sup_{0 \leq s \leq t} |\tilde{\phi}(s)| + \|\tilde{\phi}_0\|_{\mathfrak{B}_h} \\ &\leq \eta(r + M_1|\phi(0)|) + \|\phi\|_{\mathfrak{B}_h} \\ &\triangleq r_1, \end{aligned} \quad (14)$$

$$\begin{aligned} |u(t)| &= \left| W^{-1} \left\{ x_1 - T(b) [\phi(0) - g(0, \phi)] \right. \right. \\ &\quad - g(b, x_b) - \int_0^b AT(b-\xi)g(\xi, x_\xi) d\xi \\ &\quad - \int_0^b T(b-\xi)f(\xi) d\xi \\ &\quad \left. \left. - \sum_{k=1}^m T(b-t_k)\mathcal{F}_k(x(t_k^-)) \right\} (t) \right| \\ &\leq M_3 \left[|x_1| + M_1(|\phi(0)| + |g(0, \phi)|) \right. \\ &\quad + |g(b, x_b)| + M_1b(a_1r_1 + a_2) \\ &\quad \left. + M_1 \int_0^b |f(\xi)| d\xi + M_1 \sum_{k=1}^m |\mathcal{F}_k(x(t_k^-))| \right] \\ &\leq M_3 \left[|x_1| + M_1(|\phi(0)| + |g(0, \phi)|) \right. \\ &\quad + b_1r_1 + b_2 + M_1b(a_1r_1 + a_2) \\ &\quad \left. + M_1 \int_0^b \varphi(\xi) \psi(\|x_\xi\|_{\mathfrak{B}_h}) ds + M_1 \sum_{k=1}^m \alpha_k \right]. \end{aligned} \quad (15)$$

Then we have

$$\begin{aligned} |\mathcal{F}_1 y(t)| &\leq |T(t)g(0, \phi)| + |g(t, x_t)| \\ &\quad + \int_0^t |AT(t-s)g(s, x_s)| ds \\ &\quad + \int_0^t |T(t-s)f(s)| ds \end{aligned}$$

$$\begin{aligned}
 & + \int_0^t |T(t-s)(Bu)(s)| ds \\
 & + \sum_{0 < t_k < t} |T(t-t_k) \mathcal{F}_k(x(t_k^-))| \\
 \leq & M_1 |g(0, \phi)| + M_1 b(a_1 r_1 + a_2) \\
 & + M_1 \int_0^b \varphi(s) \psi(\|x_s\|_{\mathfrak{B}_h}) ds \\
 & + bM_1 M_2 M_3 \\
 & \times \left[|x_1| + M_1 (|\phi(0)| + |g(0, \phi)|) \right. \\
 & \quad + (1 + bM_2) (a_1 \|x_b\|_{\mathfrak{B}_h} + a_2) \\
 & \quad + M_1 \int_0^b \varphi(s) \psi(\|x_s\|_{\mathfrak{B}_h}) ds \\
 & \quad \left. + M_1 \sum_{k=1}^m \alpha_k \right] + M_1 \sum_{k=1}^m \alpha_k \\
 \leq & M_1 |g(0, \phi)| + (1 + bM_2) (a_1 r_1 + a_2) \\
 & + M_1 \psi(r_1) \int_0^b \varphi(s) ds + bM_1 M_2 M_4 \\
 & \times \left[|x_1| + M_1 (|\phi(0)| + |g(0, \phi)|) \right. \\
 & \quad + b_1 r_1 + b_2 + M_1 b(a_1 r_1 + a_2) \\
 & \quad \left. + M_1 \psi(r_1) \int_0^b \varphi(s) ds + M_1 \sum_{k=1}^m \alpha_k \right] \\
 & + M_1 \sum_{k=1}^m \alpha_k \\
 \triangleq & M_4.
 \end{aligned} \tag{16}$$

Consequently, $\|\mathcal{F}_1 y(t)\|_{\mathfrak{B}_b} \leq M_4$.

(II) \mathcal{F}_1 is convex on \mathfrak{B}_r . Let $y \in \{\mathfrak{B}_r\}$ and $z_1, z_2 \in \mathcal{F}_1 y$, there must be $f_1, f_2 \in S_{F,x}$ and $\mathcal{F}_k^1, \mathcal{F}_k^2 \in I_k(x(t_k^-))$, such that

$$\begin{aligned}
 z_y = & -T(t)g(0, \phi) + g(t, x_t) \\
 & + \int_0^t AT(t-s)g(s, x_s) ds \\
 & + \int_0^t T(t-s)f_\gamma(s) ds \\
 & + \int_0^t T(t-s)BW^{-1}
 \end{aligned}$$

for $\gamma = 1, 2$. Then for any $\tau \in [0, 1]$, we have

$$\begin{aligned}
 & [\tau z_1 + (1 - \tau) z_2](t) \\
 & = -T(t)g(0, \phi) + g(t, x_t) \\
 & + \int_0^t AT(t-s)g(s, x_s) ds \\
 & + \int_0^t T(t-s)[\tau f_1 + (1 - \tau) f_2](s) ds \\
 & + \int_0^t T(t-s)BW^{-1} \\
 & \times \{x_1 - T(b)[\phi(0) - g(0, \phi)] \\
 & \quad - g(b, x_b) - \int_0^b AT(b-\xi)g(\xi, x_\xi) d\xi \\
 & \quad - \int_0^b T(b-\xi)[\tau f_1 + (1 - \tau) f_2](\xi) d\xi \\
 & \quad - \sum_{k=1}^m T(b-t_k) \\
 & \quad \times [\tau \mathcal{F}_k^1 + (1 - \tau) \mathcal{F}_k^2](x(t_k^-))\} (s) ds \\
 & + \sum_{0 < t_k < t} T(t-t_k) [\tau \mathcal{F}_k^1 + (1 - \tau) \mathcal{F}_k^2](x(t_k^-)) (s) ds.
 \end{aligned} \tag{18}$$

Combining $S_{F,x}$ and $I_k(x(t_k^-))$ is convex, and \mathcal{F}_1 is convex.

(III) \mathcal{F}_1 is closed on \mathfrak{B}_r . Let $y \in \{\mathfrak{B}_r\}$. Here we should proof that if there are sequences $\{z_n\}$ satisfying $z_n \rightarrow z^*$ and $z_n \in \mathcal{F}_1 y$, then $z^* \in \mathcal{F}_1 y$ holds.

For every $z_n \in \mathcal{F}_1 y$, there is a $f_n \in S_{F,x}$ and a $\mathcal{F}_k^n \in I_k(x(t_k^-))$, such that

$$\begin{aligned}
 z_n = & -T(t)g(0, \phi) + g(t, x_t) \\
 & + \int_0^t AT(t-s)g(s, x_s) ds \\
 & + \int_0^t T(t-s)f_n(s) ds
 \end{aligned}$$

$$\begin{aligned}
 & + \int_0^t T(t-s) BW^{-1} \times \left[BW^{-1} \left(\int_0^b T(b-\xi) (f_n(\xi) - f^*(\xi)) d\xi \right) \right. \\
 & \times \left\{ x_1 - T(b) [\phi(0) - g(0, \phi)] \right. \\
 & \quad - g(b, x_b) - \int_0^b AT(b-\xi) g(\xi, x_\xi) d\xi \\
 & \quad - \int_0^b T(b-\xi) f_n(\xi) d\xi \\
 & \quad \left. \left. - \sum_{k=1}^m T(b-t_k) \mathcal{J}_k^n(x(t_k^-)) \right\} (s) ds \right. \\
 & \quad \left. + \sum_{0 < t_k < t} T(t-t_k) \mathcal{J}_k^n(x(t_k^-)) \right] \\
 & \quad + \sum_{0 < t_k < t} T(t-t_k) (\mathcal{J}_k^n(x(t_k^-)) - \mathcal{J}_k^*(x(t_k^-))) \longrightarrow 0,
 \end{aligned} \tag{19}$$

And for z^* , we should prove that there must be some $f^* \in S_{F,x}$ and some $\mathcal{J}_k^* \in I_k(x(t_k^-))$, such that

$$\begin{aligned}
 z^* & = -T(t) g(0, \phi) + g(t, x_t) \\
 & + \int_0^t AT(t-s) g(s, x_s) ds \\
 & + \int_0^t T(t-s) f^*(s) ds \\
 & + \int_0^t T(t-s) BW^{-1} \\
 & \times \left\{ x_1 - T(b) [\phi(0) - g(0, \phi)] \right. \\
 & \quad - g(b, x_b) - \int_0^b AT(b-\xi) g(\xi, x_\xi) d\xi \\
 & \quad - \int_0^b T(b-\xi) f^*(\xi) d\xi \\
 & \quad \left. \left. - \sum_{k=1}^m T(b-t_k) \mathcal{J}_k^*(x(t_k^-)) \right\} (s) ds \right. \\
 & \quad \left. + \sum_{0 < t_k < t} T(t-t_k) \mathcal{J}_k^*(x(t_k^-)) \right.
 \end{aligned} \tag{20}$$

Considering calculation of (20) subtracting (19), we get

$$\begin{aligned}
 z^* - z_n & \\
 & = \int_0^t T(t-s)
 \end{aligned}$$

Meanwhile I_k is a closed multi-valued map, there truly exists some $\mathcal{J}_k^* \in I_k(x(t_k^-))$ for (20).

Accordingly, (21) can be transformed to

$$\begin{aligned}
 & \int_0^t T(t-s) \left[BW^{-1} \left(\int_0^b T(b-\xi) (f_n - f^*)(\xi) d\xi \right) \right. \\
 & \quad \left. + (f_n - f^*) \right] (s) ds \longrightarrow 0, \quad n \longrightarrow +\infty.
 \end{aligned} \tag{22}$$

We construct a linear and continuous operator like

$$\begin{aligned}
 \Gamma & : L^1(J, X) \\
 & \longrightarrow C(J, X); \Gamma \circ S_F(x) \\
 & = \Gamma(f)(t) = \int_0^t T(t-s) \left[BW^{-1} \left(\int_0^b T(b-\xi) f(\xi) d\xi \right) \right. \\
 & \quad \left. \times (s) + f(s) \right] ds,
 \end{aligned} \tag{23}$$

moreover,

$$\|\Gamma(f)(t)\|_{L^1} \leq (bM_1M_2M_3 + 1) M_1 \|f\|_{L^1}. \tag{24}$$

From Lemma 7, $\Gamma \circ S_F$ is a closed graph operator. Then (22) implies that $\int_0^t T(t-s)[BW^{-1}(\int_0^b T(b-\xi)f^*(\xi)d\xi)(s) + f^*(s)]ds \in \Gamma(S_{F,x})$, with $f^* \in S_{F,x}$.

From the foregoing, (20) holds, which means $z^* \in \mathcal{F}_1 y$. Thus \mathcal{F}_1 is closed.

The proof is thus completed. \square

Theorem 10. Assume that hypotheses (A_0) – (A_5) hold, and

$$\begin{aligned}
 & M_1 |g(0, \phi)| + b_1 r_1 + b_2 + M_1 b (a_1 r_1 + a_2) \\
 & + M_1 \psi(r_1) \int_0^b \varphi(s) ds + b M_1 M_2 M_3 \\
 & \times \left[|x_1| + M_1 (|\phi(0)| + |g(0, \phi)|) \right. \\
 & \quad + b_1 r_1 + b_2 + M_1 b (a_1 r_1 + a_2) \\
 & \quad \left. + M_1 \psi(r_1) \int_0^b \varphi(s) ds + M_1 \sum_{k=1}^m \alpha_k \right] \\
 & + M_1 \sum_{k=1}^m \alpha_k < r,
 \end{aligned} \tag{25}$$

then system (1) is controllable on J under control function (9).

Proof. First, \mathcal{F}_1 is a condensing map on \mathfrak{B}_b^0 . Considering Remark 5, we just have to prove that for any bounded subset E of \mathfrak{B}_b^0 , $\text{diam}(\mathcal{F}_1(E)) < \text{diam}(E)$. It is obvious, because $\|\mathcal{F}_1 x(t)\| \leq M_4 < r = \text{diam}(\mathfrak{B}_r)$ for any $x(t) \in \mathfrak{B}_r$ by combining inequalities (19) and (25).

Second, here we show that the set $\Omega = \{y \in \mathfrak{B}_b^0 : \lambda y \in \mathcal{F}_1 y \text{ for some } \lambda > 1\}$ is bounded. Let $y \in \Omega$, then there are $f \in S_{F,x}$ and $\mathcal{I}_k \in I_k(x(t_k^-))$, such that

$$\begin{aligned}
 y(t) = \frac{1}{\lambda} & \left[-T(t)g(0, \phi) + g(t, x_t) \right. \\
 & + \int_0^t AT(t-s)g(s, x_s) ds \\
 & + \int_0^t T(t-s)f(s) ds \\
 & + \int_0^t T(t-s)(Bu)(s) ds \\
 & \left. + \sum_{0 < t_k < t} T(t-t_k) \mathcal{I}_k(x(t_k^-)) \right].
 \end{aligned} \tag{26}$$

So $|y(t)| \leq (1/\lambda)M_4 < M_4$. Due to Lemma 6, \mathcal{F}_1 has a fixed point in \mathfrak{B}_r . Consequently, \mathcal{F} has a fixed point, which means system (1) is controllable.

The proof is thus completed. □

Remark 11. In case $\{I_k\}$ in system (1) are single-valued maps, then the system (1) degenerates into the system (1.1) in [11]. Accordingly, our degenerated assumptions for the controllability Theorem 3.1 [11] are less conservative, which means the following: firstly, the hypothesis $(H_4)(i)$ [11] is unnecessary; secondly, the very complex hypothesis (H_6) [11] can be replaced by inequality (25); finally, the assumption $|AT| \leq M_2$ [11] is replaced by $\|Ag(t, \chi)\| \leq a_1 \|\chi\|_{\mathfrak{B}_h} + a_2$, so A is not necessary to be bounded; otherwise, our results can only be applied to finite Banach spaces [29].

4. Conclusion

In this paper, we have investigated the controllability of impulsive neutral functional differential inclusions in Banach spaces. Based on a fixed point theorem with regard to condensing map, sufficient conditions for the controllability of the impulsive neutral functional differential inclusions in Banach spaces have been derived. Moreover, a remark has been given to explain less conservative criteria for special cases. We have found an effective method to solve the controllability problem of impulsive neutral functional differential inclusions with multi-valued jump sizes in Banach spaces. Work has been improved in the previous literature.

Acknowledgments

The authors would like to thank the editor and the reviewers for their constructive comments and suggestions which improved the quality of the paper. This work is supported by the National Science Foundation of China under Grant 61174039.

References

- [1] Q. Lin and J. G. Rokne, “Inclusion isotonicity for circular centered forms in several complex variables,” *Journal of the Franklin Institute B*, vol. 335, no. 6, pp. 1069–1076, 1998.
- [2] A. J. Berry, L. V. Danyushevsky, H. S. C. O’Neill, M. Newville, and S. R. Sutton, “Oxidation state of iron in komatiitic melt inclusions indicates hot Archaean mantle,” *Nature*, vol. 455, no. 7215, pp. 960–963, 2008.
- [3] J. M. Sunshine, H. C. Connolly, T. J. McCoy, S. J. Bus, and L. M. La Croix, “Ancient asteroids enriched in refractory inclusions,” *Science*, vol. 320, no. 5875, pp. 514–517, 2008.
- [4] R. C. Loxton, K. L. Teo, V. Rehbock, and W. K. Ling, “Optimal switching instants for a switched-capacitor DC/DC power converter,” *Automatica*, vol. 45, no. 4, pp. 973–980, 2009.
- [5] S. G. Peng and L. P. Yang, “Global exponential stability of impulsive functional differential equations via Razumikhin technique,” *Abstract and Applied Analysis*, vol. 2010, Article ID 987372, 11 pages, 2010.
- [6] M. Perestyuk and P. Feketa, “Invariant sets of impulsive equations with particularities in ω -limit set,” *Abstract and Applied Analysis*, vol. 2011, Article ID 970469, 14 pages, 2011.
- [7] C. Li, J. Sun, and R. Sun, “Stability analysis of a class of stochastic differential delay equations with nonlinear impulsive effects,” *Journal of the Franklin Institute. Engineering and Applied Mathematics*, vol. 347, no. 7, pp. 1186–1198, 2010.
- [8] Q. Lin, R. Loxton, K. L. Teo, and Y. H. Wu, “A new computational method for optimizing nonlinear impulsive systems,” *Dynamics of Continuous, Discrete & Impulsive Systems B*, vol. 18, no. 1, pp. 59–76, 2011.
- [9] C. Jiang, K. L. Teo, R. Loxton, and G.-R. Duan, “A neighboring extremal solution for an optimal switched impulsive control problem,” *Journal of Industrial and Management Optimization*, vol. 8, no. 3, pp. 591–609, 2012.
- [10] N. U. Ahmed, “Systems governed by impulsive differential inclusions on Hilbert spaces,” *Nonlinear Analysis. Theory, Methods & Applications A*, vol. 45, no. 6, pp. 693–706, 2001.

- [11] B. Liu, "Controllability of impulsive neutral functional differential inclusions with infinite delay," *Nonlinear Analysis. Theory, Methods & Applications A*, vol. 60, no. 8, pp. 1533–1552, 2005.
- [12] X. Yu, X. Xiang, and W. Wei, "Solution bundle for a class of impulsive differential inclusions on Banach spaces," *Journal of Mathematical Analysis and Applications*, vol. 327, no. 1, pp. 220–232, 2007.
- [13] N. Abada, M. Benchohra, and H. Hammouche, "Existence and controllability results for impulsive partial functional differential inclusions," *Nonlinear Analysis. Theory, Methods & Applications A*, vol. 69, no. 9, pp. 2892–2909, 2008.
- [14] N. Abada, M. Benchohra, and H. Hammouche, "Existence and controllability results for nondensely defined impulsive semilinear functional differential inclusions," *Journal of Differential Equations*, vol. 246, no. 10, pp. 3834–3863, 2009.
- [15] S. Djebali, L. Górniewicz, and A. Ouahab, "First-order periodic impulsive semilinear differential inclusions: existence and structure of solution sets," *Mathematical and Computer Modelling*, vol. 52, no. 5-6, pp. 683–714, 2010.
- [16] J. Henderson and A. Ouahab, "Impulsive differential inclusions with fractional order," *Computers & Mathematics with Applications*, vol. 59, no. 3, pp. 1191–1226, 2010.
- [17] J. Y. Park, S. H. Park, and Y. H. Kang, "Controllability of second-order impulsive neutral functional differential inclusions in Banach spaces," *Mathematical Methods in the Applied Sciences*, vol. 33, no. 3, pp. 249–262, 2010.
- [18] J. Respondek, "Numerical approach to the non-linear diophantine equations with applications to the controllability of infinite dimensional dynamical systems," *International Journal of Control*, vol. 78, no. 13, pp. 1017–1030, 2005.
- [19] N. A. Karatueva and R. V. Kharchenko, "Problems of control for immunological models," *Nonlinear Analysis. Real World Applications*, vol. 7, no. 4, pp. 829–840, 2006.
- [20] K. Sakthivel, K. Balachandran, and S. S. Sritharan, "Exact controllability of nonlinear diffusion equations arising in reactor dynamics," *Nonlinear Analysis. Real World Applications*, vol. 9, no. 5, pp. 2029–2054, 2008.
- [21] J. S. Respondek, "Approximate controllability of the n -th order infinite dimensional systems with controls delayed by the control devices," *International Journal of Systems Science*, vol. 39, no. 8, pp. 765–782, 2008.
- [22] R. Manzanilla, L. G. Marmol, and C. J. Vanegas, "On the controllability of differential equation with delayed and advanced arguments," *Abstract and Applied Analysis*, vol. 2010, Article ID 307409, 16 pages, 2010.
- [23] S. Zhao and J. Sun, "Controllability and observability for impulsive systems in complex fields," *Nonlinear Analysis. Real World Applications*, vol. 11, no. 3, pp. 1513–1521, 2010.
- [24] X. Wan and J. Sun, "Approximate controllability for abstract measure differential systems," *Systems & Control Letters*, vol. 61, no. 1, pp. 50–54, 2012.
- [25] M. Martelli, "A Rothe's type theorem for non-compact acyclic-valued maps," *Bollettino dell'Unione Matematica Italiana*, vol. 11, no. 4, pp. 70–76, 1975.
- [26] L. Górniewicz, S. K. Ntouyas, and D. O'Regan, "Controllability of semilinear differential equations and inclusions via semigroup theory in Banach spaces," *Reports on Mathematical Physics*, vol. 56, no. 3, pp. 437–470, 2005.
- [27] B. C. Dhage, "Periodic boundary value problems of first order ordinary Caratheodory and discontinuous differential equations," *Nonlinear Functional Analysis and Applications*, vol. 13, no. 2, pp. 323–352, 2008.
- [28] A. Lasota and Z. Opial, "An application of the Kakutani-Ky Fan theorem in the theory of ordinary differential equations," *Bulletin de l'Académie Polonaise des Sciences*, vol. 13, pp. 781–786, 1965.
- [29] E. Hernández, "Existence results for partial neutral functional integrodifferential equations with unbounded delay," *Journal of Mathematical Analysis and Applications*, vol. 292, no. 1, pp. 194–210, 2004.

Copyright of Abstract & Applied Analysis is the property of Hindawi Publishing Corporation and its content may not be copied or emailed to multiple sites or posted to a listserv without the copyright holder's express written permission. However, users may print, download, or email articles for individual use.